

6164US

CUSTOM ALPHA DISPLAY KEYPAD
WITH FOUR INTEGRATED
HARDWIRED ZONES



Honeywell's 6164US Custom Alpha keypad with four integrated hardwired zones helps reduce install, material and inventory costs. This keypad is ideal for applications where you need to protect areas like a front door or foyer without incurring the costs of hardwiring that point back to the control panel. The 6164US also has an on-board relay to help facilitate lighting and garage door control.

FEATURES

- Custom alpha display
- Four hardwired zones built-in
- One on-board relay
- Keys continuously backlit for greater visibility
- Speaker with audible beeps to indicate:
 - System status
 - Entry/exit delay
 - Other alarm situations
- Zones and system events displayed in plain English
- No confusing blinking lights
- Four programmable function keys
- System functions clearly labeled
- Functions performed by just entering security code plus command
- White with removable door blends with any décor

SPECIFICATIONS

Physical

- 5-5/16"H x 7-3/8"W x 1-3/16"D
(135mm x 190mm x 30mm)

Current

- Standby-40mA
- Activated Transmission-160mA

Wiring

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data in" to control panel
- D0 (Yellow): "Data out" from control panel

Compatibility

- Fully compatible with all VISTA controls

ORDERING

6164US

Custom alpha display keypad with four integrated hardwired zones

Honeywell Security & Custom Electronics

Honeywell
2 Corporate Center Drive Suite 100
P.O. Box 9040
Melville, NY 11747

www.honeywell.com

L/6164US/D
July 2007
© 2007 Honeywell International Inc.

Honeywell